

Programming Lights with the Lightronics TL-5024, New Hope Church Feb. 2011

<http://www.lightronics.com/pdfs/tl5024m.pdf>

Quick Mix Lower Stage (Cue 3 and all odd after 3)

Y Mode = Scene

Adjust faders for Lower2 + LED1RBG + LED2RBG + Par38

Press RECORD

Press BUMP button for Lower1

Lower1 is now recorded for the Cue

Quick Mix Upper Stage (Cue 2, all even cues)

Y Mode = Scene

Adjust faders for Upper2 + LED1RBG + LED2RBG + Par38

Press RECORD

Press BUMP button for Upper1

Upper is now recorded for the Cue

Quick Mix Pre Service (Cue1)

Y Mode = CHAN 13-24

Adjust faders for lights as needed

Press RECORD

Press BUMP button for Pre (Scene 3)

Pre Service is now recorded for the Cue

Communion Light

Y Mode = CHAN 13-24

Adjust channel 24 as needed

BANK #1 - Pre - programmed Scenes (Y Mode = Scene)



Scene#	Description
1	Lower stage 1, in Cue stack
2	Upper stage 1, in Cue stack
3	Pre Service, Cue #1
4	Lower stage 2, no background, use to make Lower stage 1
5	Upper stage 2, no background, use to make Upper stage 1
6	LED1 Red
7	LED1 Green
8	LED1 Blue
9	LED2 Red
10	LED2 Green
11	LED2 Blue
12	Par 38 Floor Lights

CUE LIST

Bank 1

0 Blackout

1 Preservice/offering

2,4,6,8,10,12 Upper Stage w/ 2 sec fade

14,16,18,20 Upper Stage w/ 4 sec fade

3,5,7,9,11,13 Lower Stage w/ 2 sec fade

15,17,19,21 Lower Stage w/ 4 sec fade

Patch List by Channel

Channel	Description	Dimmer	Channel	Description	Dimmer
1	LED 1 Level	17	13	Upper Center Par 56 500w N	2
2	LED 1 Red	18	14	Upper Center Par 56 500w N	3
3	LED1 Green	19	15	Upper Right Par 56 500w N	9
4	LED1 Blue	20	16	Upper Right Par 56 500w N	10
5	LED 2 Level	21	17	Upper Right Par 56 500w N	11
6	LED 2 Red	22	18	Upper Right Par 56 500w N	12
7	LED2 Green	23	19	Lower Spot Leko 575w	4
8	LED2 Blue	24	20	Lower Right Par 56 500w N	13
9	Older Floor Lights Par 38 100w N	25/26/27/28	21	Lower Right Par 56 500w N	14
10	Upper Left Par 56 500w N	6	22	Lower Right Par 56 500w N	15
11	Upper Left Par 56 500w N	7	23	Lower Left Par 56 500w N	16
12	Upper Left Par 56 500w N	8	24	Communion Par 56 500w N	1
99	Audience Lighting 5 x Par 38 100w F	5			

Lighting Layout NHC 2011



All Dimmers

Lighttronics AS40L

4 x 600 watts

Fuses

5 amp - 250vac

Fast Blow

